

smsng-g7 VESA adapter (V3)

Assembly instructions

The VESA adapter is compatible with monitors from the Samsung (samsung.com) Odyssey G6, G7, G8, neo G8, G9, neo G9 series and other models:

C27G73TQSR, C32G73, C49G94TSSR, C49G95T, C49G95TSSRXEN, C49HG90DMU, C49J890DKR, C49J890DKU, C49J890DKUXEN, C49RG90, C49RG90SSI, C49RG90SSN, C49TG90, C49UG90, C49UG90DMR, CHG90, CRG9, G6, G65B, G7, G70A, G70B, G70NC, G73TF, G75, G75T, G7A, G85NB, G9, G95A, G95NA, G95NC, G95T, LC27G74TQSR, LC27G75TQ,, LC27G75TQSEXXP, LC27G75TQSEXXP, LC27G75TQSNXZA, LC27G75TQSNXZA, LC27G75TQSRXEN, LC27G75TQSRXEN, LC32G75T, LC32G75TQ, LC49G95T, LC49G95TSSRXEN, LC49G97T, LC49G97TSSNXDC, LC49J890DKEXXY, LC49J890DKUXEN, LC49RG90SSIXCI, LC49RG90SSNXZA, LC49RG90SSRXUF, LC49RG90SSUXEN, LC49UG90DMEXXM, LS32BG85, LS32BG850, LS32BG850NUXEN, LS32BG850NUXXU, LS32BG852NNXGO, LS49C954U, LS49C954UAKXKR, LS49CY955ENXZA, LS49CY955EUXEN, LS49KG954ECXZW, LS57CG952NNXZA, Odyssey G8, Odyssey Neo G8, S32BG85, S32BG850, S49A950U, S49A950UIN, S49A950UIU, S49AG952NN, S49AG95NC, S49C954U, S57C952NN, S95UC, neo G7, neo G9

WARNING

To minimize the risk of injury, it is important to read all instructions carefully before installation. We accept no liability for personal injury or damage to property caused by improper use of this product. It is also essential to observe the technical specifications of the product.



1. Read all instructions carefully.

- 2.** Incorrect installation can lead to damage or serious injury. Make sure that the product and the monitor are securely mounted before using it. 3.
- 3.** Make sure that the bracket to which the product is attached can easily support the total weight of the monitor, computer and adapter.

Technical Specifications

- **Maximum load capacity:** 17 kg / 37.5 lbs
- **VESA standard compatibility:** 75x75 mm
- **Material:** Plastic
- **Pivot angle:** 90°
- **Maximum operating temperature:** 35°C / 95°F
- **Maximum ambient temperature:** 35°C / 95°F

Important Safeguards



Please read this manual carefully and keep it for future reference. If you pass the product on to third parties, this manual should always be included. Ignoring these instructions may result in injuries or damage to people and products, for which we cannot accept any liability.

IMPORTANT - KEEP FOR FUTURE REFERENCE.

- The use of this product should always be in accordance with the specified safety instructions.
- Do not install your VESA adapter in combination with the monitor in places where people are located below.
- Do not exceed the maximum weight of the compatible monitor models, as this may result in serious injuries or property damage.
- Pay attention to the maximum ambient temperature of 35°C when using the product.
- Do not mount the VESA adapter near a heat source or in direct sunlight, as this may cause the adapter to overheat.
- Check if your mounting point (e.g., monitor arm) can support the weight of the monitor with the VESA adapter.
- The product is designed exclusively for mounting with a hole pattern of 75x75 / 100x100mm / 200x200mm.
- After installing the VESA adapter, the position of the monitor must be readjusted to ensure proper ergonomics.

WARNING

Ensure that the device is turned off and disconnected from the power supply before installation to avoid possible injuries or damage.

1. Before First Use

Check the product carefully for possible transport damage and for the absence of accessories, such as screws, which should be included in the scope of delivery.

CAUTION

Make sure that packaging materials and small screws and parts contained therein are inaccessible to children to minimize the risk of choking and other risks.

2. Maintenance and Cleaning

2.1 Maintenance

- It is recommended to check every three months that all screws are still tight. Also, regularly check the condition of all components of the product.
- Store the product in a cool and safe place, ideally at a maximum storage temperature of 40°C. For additional safety, keep the product away from children and preferably in its original packaging.
- Avoid any vibrations and shocks so as not to affect the life and functionality of the product.

2.2 Cleaning

- No corrosive or hot cleaning agents should be used to clean the product. Likewise, wire brushes, metal or other sharp materials are unsuitable for cleaning and should not be used.
- For gentle and effective cleaning, the use of a soft, damp cloth is recommended.

3. Waste Disposal

For the disposal of this product we recommend to contact the responsible local authorities or disposal services. They can provide you with detailed information on available disposal options and recycling centers in your area.

4. Manufacturer Information

3idee S.à r.l.
19 Rue de Bitbourg
L-1273 Luxembourg
Luxembourg


mail: info@3idee.eu

5. Help and Feedback


If you need help with your article, we are here for you. We also appreciate any feedback.

<https://help.3idee.eu/en/contact>

Scope of Delivery Accessories




1x smsng-g7-part1




1x smsng-g9-part2



4x M4x60 Screw with cross recess (**SP60**)



4x M4x40 Screw with cross recess (**SP13**)



4x M4x14 Screw with cross recess (**SP2**)

⚠ NOTE: Please check that all parts of the accessories are complete before assembly. If anything is missing, please contact our customer service team immediately by email or phone. We will be happy to help you.

Horizontal / Vertical Alignment

Please note: Not all VESA adapters and monitors are designed for vertical (upright) orientation. This limitation is often due to the specific geometry of the adapter or monitor. Do not ignore this information, as the load limit of the adapter can quickly be exceeded if not installed properly.


We are continuously working on developing monitors and adapters that are also suitable for vertical orientation.

However, monitors are designed for horizontal alignment by default.

**Horizontal
Mounting: YES**



Vertical mounting: YES



Assembly Instruction

Step 1

To get the best possible mounting, please check if your Samsung monitor belongs to **Option A** or **Option B** models.

Option A: G6, G65B, G7, NEO G7, G7A, G70A, G70B, G70NC, G73TF, G75, G75T, CRG9, CHG90, G94T, G95T

Option B: G8, neo G8, G9, neo G9

To ensure an optimal user experience, you should check whether you need the extension piece (**smsng-g9-part2**) or not.

Step 2 (Option A)

Take the screws from **SP13** and attach the VESA adapter to the mounting of your monitor as shown. (Figure 1)

Tighten all 4 screws.




Figure 1

Step 2 (Option B)

Take the screws from **SP60** and attach the VESA adapter and the extension piece to the mounting of your monitor as shown. (Figure 2)

Tighten all 4 screws.




Figure 2

Step 3 (Option A)

Please check that all 4 screws are properly tightened. (Figure 3)




Figure 3

Step 3 (Option B)

Please check that all 4 screws are properly tightened (Figure 4)




Figure 4

Step 4

⚠ NOTE: If the instructions in this step are not suitable for your device, please follow the mounting guidelines of the manufacturer of your monitor arm or swivel arm to mount the monitor to the wall or swivel arm.

We recommend a **second person** for this step.

Now lift the monitor and hold it against your monitor mount. Attach the VESA adapter using the 4 M4x14 screws supplied (**screw bag: SP2**).

It is best to fasten 2 screws diagonally first so that the monitor can no longer fall down and you can fasten the remaining screws easily.

⚠ NOTE: Make sure you use the right screws!

(Figure 5)




Figure 5

Step 5

Please make sure that all 4 screws are tight. (Figure 6)




Figure 6